

Voor een perfecte werking van de SPA 112 op de Wizard series der telefoons, dient U volgende settings aan te passen.

Pour réaliser un fonctionnement parfait du SPA112 sur nos portiers de rue Wizard , vous devez changer les paramètres suivant :

1) regional settings → Call progress tones

Dial Tone:	425@-16;10(*0/1)
Second Dial Tone:	425@-16,425@-16;10(*0/1+2)
Outside Dial Tone:	425@-16;10(*0/1)
Prompt Tone:	425@-16,425@-16;10(*0/1+2)
Busy Tone:	425@-16,425@-16;10(.5/.5/1+2)
Reorder Tone:	425@-16,425@-16;10(.5/.5/1+2)
Off Hook Warning Tone:	425@-16,425@-16;10(.5/.5/1+2)
Ring Back Tone:	425@-16,425@-16;*(1/3/1+2)
Ring Back 2 Tone:	425@-16,425@-16;*(1/3/1+2)
Confirm Tone:	600@-16;1(.25/.25/1)
SIT1 Tone:	985@-16,1428@-16,1777@-16;20(.380/0/1,.380/0/2,.380/0/3,0/4/0)
SIT2 Tone:	914@-16,1371@-16,1777@-16;20(.274/0/1,.274/0/2,.380/0/3,0/4/0)
SIT3 Tone:	914@-16,1371@-16,1777@-16;20(.380/0/1,.380/0/2,.380/0/3,0/4/0)
SIT4 Tone:	985@-16,1371@-16,1777@-16;20(.380/0/1,.274/0/2,.380/0/3,0/4/0)
MWI Dial Tone:	350@-19,440@-19;2(.1/.1/1+2);10(*0/1+2)
Cfwd Dial Tone:	350@-19,440@-19;2(.2/.2/1+2);10(*0/1+2)
Holding Tone:	600@-19;*(.1/.1/1,.1/.1/1,.1/9.5/1)
Conference Tone:	425@-19;20(.1/.1/1,.1/9.7/1)
Secure Call Indication Tone:	397@-19,507@-19;15(0/2/0,.2/.1/1,.1/2.1/2)
Feature Invocation Tone:	425@-16;*(.1/.1/1)
Call Remind Tone:	

2) regional settings → Control timer Values (interdigit Long timer= 3 ; CPC Delay =0;Reorder Delay en CPC duration =0)

Regional	Ring Voltage:	85	CWT Frequency:	440@-10
Line 1	Synchronized Ring:	no		
User 1	Control Timer Values (sec)			
Line 2	Hook Flash Timer Min:	.1	Hook Flash Timer Max:	.9
User 2	Callee On Hook Delay:	0	Reorder Delay:	2
	Call Back Expires:	1800	Call Back Retry Intvl:	30
	Call Back Delay:	.5	VMWI Refresh Intvl:	0
	Interdigit Long Timer:	3	Interdigit Short Timer:	3
	CPC Delay:	0	CPC Duration:	0

3) Line1 & Line2 settings → Audio Configuration

Quick Setup	Network Setup	Voice	Administration	Status
Information	Line 1			
System	Feature Dial Serv:	yes	Service Announcement Serv:	no
SIP	Reuse CID Number As Name:	yes		
Provisioning	Audio Configuration			
Regional	Preferred Codec:	G711a	Second Preferred Codec:	Unspecified
Line 1	Third Preferred Codec:	Unspecified	Use Pref Codec Only:	no
User 1	Use Remote Pref Codec:	no	Codec Negotiation:	Default
Line 2	G729a Enable:	yes	Silence Supp Enable:	no
User 2	G726-32 Enable:	yes	Silence Threshold:	medium